

ID	Name	Type	Constraint	Quality	Fallback	Access	Conformance
6	AverageRssi	int8	-128 to 0	X	null		M
7	LastRssi	int8	-128 to 0	X	null		M
8	FrameErrorRate	uint8	0 to 100		0		M
9	MessageErrorRate	uint8	0 to 100		0		M
10	RxOnWhenIdle	bool	all				M
11	FullThreadDevice	bool	all				M
12	FullNetworkData	bool	all				M
13	IsChild	bool	all				M

ExtAddress Field

This field SHALL specify the IEEE 802.15.4 extended address for the neighboring Node. The uint64 value is composed by taking the 8 octets of the extended address EUI-64 and treating them as a big-endian integer. For example, octet string (in hexadecimal, from first octet to last) **00112233AABBCCDD** would lead to a value of 0x00112233AABBCCDD.

Age Field

This field SHALL specify the duration of time, in seconds, since a frame has been received from the neighboring Node.

Rloc16 Field

This field SHALL specify the RLOC16 of the neighboring Node. The uint16 value is composed by taking the two RLOC16 and treating the octet string as if it was encoding a big-endian integer. For example, octet string (in hexadecimal, from first octet to last) **44AA** would lead to a value of 0x44AA.

LinkFrameCounter Field

This field SHALL specify the number of link layer frames that have been received from the neighboring node. This field SHALL be reset to 0 upon a reboot of the Node.

MleFrameCounter Field

This field SHALL specify the number of Mesh Link Establishment frames that have been received from the neighboring node. This field SHALL be reset to 0 upon a reboot of the Node.