

11.14.6.59. Delay Attribute

This attribute SHALL be null when there is no dataset configured.

11.14.6.60. SecurityPolicy Attribute

This attribute SHALL indicate the current security policies for the Thread partition to which a Node is connected. This attribute SHALL be null when there is no dataset configured.

11.14.6.61. ChannelPage0Mask Attribute

This attribute SHALL indicate the channels within channel page 0, in the 2.4GHz ISM band. The channels are represented in most significant bit order, with bit value 1 meaning selected, bit value 0 meaning unselected. For example, the most significant bit of the left-most byte indicates channel 0. If channel 0 and channel 10 are selected, the mask would be: 80 20 00 00. This attribute SHALL be null when there is no dataset configured.

11.14.6.62. OperationalDatasetComponents Attribute

This attribute SHALL indicate a collection of flags to indicate the presence of various operationally acquired values.

11.14.6.63. ActiveNetworkFaults Attribute

This attribute SHALL indicate the set of faults currently detected by the Node. When the Node detects a fault has been raised, the appropriate [NetworkFaultEnum](#) value SHALL be added to this list. This list SHALL NOT contain more than one instance of a specific [NetworkFaultEnum](#) value. When the Node detects that all conditions contributing to a fault has been cleared, the corresponding [NetworkFaultEnum](#) value SHALL be removed from this list. An empty list SHALL indicate there are currently no active faults. The order of this list SHOULD have no significance. Clients interested in monitoring changes in active faults MAY subscribe to this attribute, or they MAY subscribe to [NetworkFaultChange](#)

11.14.6.64. ExtAddress Attribute

This attribute SHALL indicate the IEEE 802.15.4 extended address for the Node. A value of null SHALL indicate that the extended address is not yet known. The uint64 value is composed by taking the 8 octets of the extended address EUI-64 and treating them as a big-endian integer. For example, octet string (in hexadecimal, from first octet to last) **00112233AABBCCDD** would lead to a value of 0x00112233AABBCCDD.

11.14.6.65. Rloc16 Attribute

This attribute SHALL indicate the RLOC16 of the Node. A value of null SHALL indicate that the Thread interface is not currently configured or operational. The uint16 value is composed by taking the two RLOC16 and treating the octet string as if it was encoding a big-endian integer. For example, octet string (in hexadecimal, from first octet to last) **44AA** would lead to a value of 0x44AA.