

Failure Value

This value SHALL indicate that the reason for a state change is the failure of a prior operation.

TimeOut Value

This value SHALL indicate that the reason for a state change is a time-out condition as determined by the OTA Requestor.

DelayByProvider Value

This value SHALL indicate that the reason for a state change is a request by the OTA Provider to await for a delay.

ProviderLocation Type

This structure encodes a [fabric-scoped](#) location of an OTA provider on a given fabric.

Access Modifier: Fabric Scoped							
ID	Name	Type	Constraint	Quality	Fallback	Access	Conformance
1	ProviderNodeID	node-id					M
2	Endpoint	endpoint-no					M

ProviderNodeID Field

This field SHALL contain the [Node ID](#) of the OTA Provider to contact within the Fabric identified by the FabricIndex.

Endpoint Field

This field SHALL contain the endpoint number which has the OTA Provider device type and OTA Software Update Provider cluster server on the ProviderNodeID. This is provided to avoid having to do discovery of the location of that endpoint by walking over all endpoints and checking their [Descriptor Cluster](#).

11.20.7.5. Attributes

ID	Name	Type	Constraint	Quality	Fallback	Access	Conformance
0x0000	DefaultOTAProviders	list[ProviderLocation]	desc	N	[]	RW F VA	M
0x0001	UpdatePossible	bool	all		True	R V	M