

11.23.6.7. DiscoveryCapabilitiesBitmask

This field SHALL identify the device's available technologies for device discovery which SHALL be encoded as defined in Table 58, "Discovery Capabilities Bitmask". This field SHALL match the Table 58, "Discovery Capabilities Bitmask" provided in the Section 5.1.3, "QR Code" (if a QR-code or NFC Tag is provided on or with the product). This field SHALL be populated if the CommissioningFallbackUrl is populated, and SHOULD be populated for all other products.

11.23.6.8. CommissioningCustomFlow

This field SHALL identify the device's commissioning flow with encoding as described in Custom Flow.

11.23.6.9. CommissioningCustomFlowUrl

This field SHALL identify a vendor-specific commissioning URL for the device model when the CommissioningCustomFlow field is set to '2', and MAY be set for other values of CommissioningCustomFlow. See Section 5.7.3, "Custom Commissioning Flow" for how this URL is used. During the lifetime of the product, the specified URL SHOULD resolve to a maintained web page. The syntax of this field SHALL follow the syntax as specified in RFC 1738 and SHALL use the https scheme. The maximum length of this field is 256 ASCII characters.

11.23.6.10. CommissioningModeInitialStepsHint

This field SHALL identify a hint for the steps that MAY be used to put a device that has not yet been commissioned into commissioning mode without factory resetting it. This field is a bitmap with values defined in the Pairing Hint Table. For example, a value of 1 (bit 0 is set) indicates that a device that has not yet been commissioned will enter Commissioning Mode upon a power cycle.

Devices that implement Extended Discovery SHALL reflect this value in the Pairing Hint field of Commissionable Node Discovery when they have not yet been commissioned.

11.23.6.11. CommissioningModeInitialStepsInstruction

This field SHALL be populated with the appropriate Pairing Instruction for those values of CommissioningModeInitialStepsHint, for which the Pairing Hint Table indicates a Pairing Instruction (PI) dependency.

Devices that implement Extended Discovery SHALL reflect this value in the Pairing Instruction field of Commissionable Node Discovery when they have not yet been commissioned.

11.23.6.12. CommissioningModeSecondaryStepsHint

This field SHALL identify a hint for the steps that MAY be used to put a device that has already been commissioned into commissioning mode without factory resetting it. This field is a bitmap with values defined in the Pairing Hint Table. At least bit 2 SHALL be set, to indicate that a current Administrator can be used to put a device that has already been commissioned into commissioning mode (see Section 5.6.3, "Enhanced Commissioning Method (ECM)"). Devices which implement *additional* mechanisms to put a device that has already been commissioned into commissioning mode without factory resetting it SHALL reflect these mechanism by setting the corresponding bits in this field.

Devices that implement Extended Discovery SHALL reflect this value in the Pairing Hint field of Commissionable Node Discovery when they have already been commissioned.