

- i. Add the corresponding **DatastoreGroupKeySetStruct** to the Node’s Group Key list.

A. If successful, mark the Status to **Committed**.

B. If not successful, update the Status to **CommitFailed** and the FailureCode to the returned error. The error SHALL be handled in a subsequent **Node Refresh**.

c. For each GroupKeySetEntry in the GroupKeySetList of the Node Information Entry with a **CommitFailure** Status:

i. A **CommitFailure** with an unrecoverable FailureCode SHALL be handled by removing the entry from the GroupKeySetList.

ii. A **CommitFailure** with a recoverable FailureCode (i.e. **TIMEOUT**, **BUSY**) SHALL be handle in a subsequent **Node Refresh**.

d. All remaining entries in the GroupKeySetList should be replaced by the remaining entries on the Node.

5. Ensure the ACLList for the Node Information Entry with the given NodeID matches the ACL attribute on the given Node. This involves the following steps:

a. Read the ACL attribute on the Node.

b. For each **DatastoreACLEntryStruct** in the ACLList of the Node Information Entry with a **Pending** Status:

i. Add the corresponding **DatastoreACLEntryStruct** to the Node’s ACL attribute.

A. If successful, mark the Status to **Committed**.

B. If not successful, update the Status to **CommitFailed** and the FailureCode to the returned error. The error SHALL be handled in a subsequent **Node Refresh**.

c. For each **DatastoreACLEntryStruct** in the ACLList of the Node Information Entry with a **CommitFailure** Status:

i. A **CommitFailure** with an unrecoverable FailureCode (i.e. **RESOURCE_EXHAUSTED**, **CONSTRAINT_ERROR**) SHALL be handled by removing the entry from the ACLList.

ii. A **CommitFailure** with a recoverable FailureCode (i.e. **TIMEOUT**, **BUSY**) SHALL be handle in a subsequent **Node Refresh**.

d. All remaining entries in the ACLList should be replaced by the remaining entries on the Node.

6. Update the CommissioningStatusEntry for the Node Information Entry to **Committed**.

11.24.7.12. UpdateNode Command

The command SHALL be used to update the friendly name for a node in the **Joint Fabric** Datastore Cluster of the accessing fabric.

The data for this command is as follows:

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	NodeID	node-id	all			M

Page 1102

Copyright © Connectivity Standards Alliance, Inc. All rights reserved.

The logo for the Connectivity Standards Alliance (CSA), featuring the letters 'csa' in a stylized blue font with the words 'connectivity standards alliance' in smaller text below it.