

Bit	Name	Summary	Conformance
0	FabricSynchronization	Aggregators which support Fabric Synchronization may be commissioned.	O

FabricSynchronization Bit

The FabricSynchronization bit SHALL be set to 1 if and only if the server supports commissioning nodes that support [Fabric Synchronization](#).

11.26.5. Attributes

ID	Name	Type	Constraint	Quality	Fallback	Access	Conformance
0x0000	Supported-DeviceCategories	Supported-DeviceCategory-Bitmap	all		0	R M	M

11.26.5.1. SupportedDeviceCategories Attribute

This attribute SHALL indicate the device categories specified in SupportedDeviceCategoryBitmap that are supported by this Commissioner Control Cluster server.

A client SHALL NOT send the RequestCommissioningApproval command if the intended node to be commissioned does not conform to any of the values specified in SupportedDeviceCategories.

11.26.6. Commands

ID	Name	Direction	Response	Access	Conformance
0x00	RequestCommissioningApproval	client ⇒ server	Y	M	M
0x01	CommissionNode	client ⇒ server	ReverseOpen-CommissioningWindow	M	M
0x02	ReverseOpenCommissioningWindow	server ⇒ client	N		M

11.26.6.1. RequestCommissioningApproval Command

This command is sent by a client to request approval for a future CommissionNode call. This is required to be a separate step in order to provide the server time for interacting with a user before informing the client that the CommissionNode operation may be successful.