

ID	Description
CM5	All Devices include a randomly generated setup passcode and a corresponding passcode verifier derived from the setup passcode via a PBKDF. The passcode includes at least 27 bits of entropy compliant with a recognized standard (e.g., NIST SP 800-90B).
CM6	Unsecured rendezvous are enabled by a user action and, upon time-out or commissioning failure, will cause deletion of any state information. Examples of "user actions" are pressing a physical button, power-cycling a Device, and leveraging a previously commissioned account.
CM7	Minimize OS and other version information advertised during discovery.
CM8	Both commissioning and unsecured rendezvous actions time-out after at most 15 minutes from the beginning of the commissioning mode when commissioning has not been concluded.
CM15	Devices have a physical button or trigger for factory reset.
CM16	Devices rotate keys at specified triggers (e.g. Factory Device Reset).
CM17	Devices implement Perfect Forward secrecy key agreement protocols that give assurances that session keys will not be compromised even if long-term secrets used in the session key exchange are compromised.
CM20	Revoke Device credentials and privileges when the Device is removed from the home.
CM21	Devices have cryptographically signed firmware, including all firmware and software on the Device.
CM22	Devices have a verified boot based in an immutable root of trust to verify the authenticity of firmware.
CM23	All Devices include a Device Attestation Certificate and private key, unique to that Device.
CM24	Manufacturers control the number of DACs issued under their Vendor ID.
CM28	Private part of code signing key is strongly protected against disclosure or misuse. For example, it could be stored in an HSM on a secure server outside the factory with very restricted access to only a small number of Device Manufacturer employees.
CM35	Factory reset removes all local data and key material created during or after commissioning except data explicitly required to persist across resets.
CM36	A Commissioner / Administrator only adds Root Certificates that it trusts to a node.
CM39	Cryptographic keys are randomly chosen using the strong entropy separately required and the cryptographic algorithms and key lengths specified by Matter.
CM41	Administrators can view the set of Fabrics on each Device (i.e., Attributes for the Node Operational Credentials Cluster).