

ID	Description
CM110	Devices support remote Firmware attestation with trusted root of measurement to allow local and cloud agents to validate the cryptographic identity of the Device firmware and refuse to perform actions on behalf of or by relying to information acquired by known compromised versions. Firmware attestation is performed at initial commissioning and when revocation lists get updated.
CM112	ACLs restrict access granted to Nodes.
CM113	Fusing of Production Devices is done correctly. For example, disabling debug interfaces, and programming trust anchors for secure boot. There are multiple options to secure fusing on the factory floor (e.g., physically securing the fusing station, pre-fusing the silicon, etc).
CM117	Design, implement, and operate the PAI and associated infrastructure so that unauthorized Devices cannot be created with proper credentials.
CM132	Use passive mode NFC and lowest power on the initiator if possible — this reduces the range of NFC making eavesdropping more difficult. Doing so, however, this will reduce the distance at which the NFC interaction will be effective and, possibly, the device setup experience.
CM133	If possible, use RSSI on at least one of the two NFC endpoints to disregard high power radiation from attackers. Attackers cannot always control the strength of the field near the legitimate endpoints if they are far away and excess power can be detected.
CM135	Packaging protects against RF devices reading passive NFC tags.
CM136	Position NFC tags to be readable only from a certain direction.
CM139	All cryptographic keys and secrets are protected against unauthorized modifications on the device, at rest and during compute. This could include protections against hardware attacks or logical attacks.
CM149	Administrators only grant privileges to a Bridge if the Administrator is comfortable granting those same privileges to all Bridged Devices behind that Bridge.
CM152	Device manufacturers provide a way to secure a static Passcode after initial commissioning so that it is not available for unauthorized agents.
CM154	A device manufacturer implements Section 5.6.2, “Basic Commissioning Method (BCM)” only for devices that adequately secure the Passcode .
CM160	Vendors sign off on some other entity posting data about their products to the DCL.
CM163	Tightly restrict access to Validator Nodes (e.g., with VPN that only permits Validator Nodes, Observer Nodes, and authenticated clients with write access).
CM166	Matter vendors run and use their own Observer Node and restrict access to it to make sure that it stays available to that company’s DCL clients.
CM167	Matter vendors protect DCL private keys in HSM equipped servers.
CM169	All parameters passed in transactions and queries to the DCL pass input validation checks.