

```

00000010 18 25 03 34 12 2c 04 13 5a 49 47 32 30 31 34 32 |.%.4.,...ZIG20142|
00000020 5a 42 33 33 30 30 30 32 2d 32 34 24 05 00 24 06 |ZB330002-24$..$.|
00000030 00 25 07 94 26 24 08 00 25 09 f1 ff 25 0a 00 80 |.%.&$..%...%...|
00000040 36 0b 10 14 78 5c e7 05 b8 6b 8f 4e 6f c7 93 aa |6...x\...k.No...|
00000050 60 cb 43 ea 69 68 82 d5 18 18 |`.C.ih....|
0000005a

```

===== Algorithm outputs =====

-> Encoded CMS SignedData of Certification Declaration (273 bytes):

```

00000000 30 82 01 0d 06 09 2a 86 48 86 f7 0d 01 07 02 a0 |0.....*.H.....|
00000010 81 ff 30 81 fc 02 01 03 31 0d 30 0b 06 09 60 86 |..0.....1.0...`.|
00000020 48 01 65 03 04 02 01 30 69 06 09 2a 86 48 86 f7 |H.e....0i...*.H..|
00000030 0d 01 07 01 a0 5c 04 5a 15 24 00 01 25 01 f2 ff |.....\Z.$..%...|
00000040 36 02 05 01 80 05 02 80 18 25 03 34 12 2c 04 13 |6.....%.4.,...|
00000050 5a 49 47 32 30 31 34 32 5a 42 33 33 30 30 30 32 |ZIG20142ZB330002|
00000060 2d 32 34 24 05 00 24 06 00 25 07 94 26 24 08 00 |-24$..$..%..&$..|
00000070 25 09 f1 ff 25 0a 00 80 36 0b 10 14 78 5c e7 05 |%...%...6...x\..|
00000080 b8 6b 8f 4e 6f c7 93 aa 60 cb 43 ea 69 68 82 d5 |.k.No...`.C.ih..|
00000090 18 18 31 7d 30 7b 02 01 03 80 14 62 fa 82 33 59 |..1}0{.....b..3Y|
000000a0 ac fa a9 96 3e 1c fa 14 0a dd f5 04 f3 71 60 30 |....>.....q`0|
000000b0 0b 06 09 60 86 48 01 65 03 04 02 01 30 0a 06 08 |...`.H.e....0...|
000000c0 2a 86 48 ce 3d 04 03 02 04 47 30 45 02 20 4a e9 |*.H.=....G0E. J.|
000000d0 c9 b7 f8 aa 68 61 0a dd 84 e4 12 91 fc 8f 4d c5 |...ha.....M.|
000000e0 33 fc a2 9d c1 ff f2 25 3c 09 cd 32 f7 75 02 21 |3.....%<..2.u.!!|
000000f0 00 9c 0a 5f de f9 e0 08 d1 cc 8b b7 c3 95 9c db |..._.....|
00000100 65 c4 61 25 cb 72 95 08 1e 47 b5 c1 31 e4 d1 f4 |e.a%.r...G..1...|
00000110 8c |.|
00000111

```

F.2. Device Attestation Response test vector

This subsection contains a worked example of the [Attestation Information](#) to be generated in the [AttestationResponse Command](#) when executing the [Device Attestation Procedure](#).

The Device Attestation key pair shown is an example, not to be reused in implementations.

NOTE

This test vector does NOT contain the optional [Firmware Information](#) payload. It is omitted.

===== Algorithm inputs =====

-> AttestationNonce (example):

```

e0:42:1b:91:c6:fd:cd:b4:0e:2a:4d:2c:f3:1d:b2:b4:e1:8b:41:1b:1d:3a:d4:d1:2a:9d:90:aa:8e
:52:fa:e2

```