

1.5.6.5. OffWaitTime Attribute

This attribute specifies the length of time (in 1/10ths second) that the Off state SHALL be guarded to prevent another OnWithTimedOff command turning the server back to its On state (e.g., when leaving a room, the lights are turned off but an occupancy sensor detects the leaving person and attempts to turn the lights back on). This attribute can be written at any time, but writing a value only has an effect when in the Timed On state followed by a transition to the Delayed Off state, or in the Delayed Off state. See [OnWithTimedOff](#) for more details.

1.5.6.6. StartUpOnOff Attribute

This attribute SHALL define the desired startup behavior of a device when it is supplied with power and this state SHALL be reflected in the OnOff attribute. If the value is null, the OnOff attribute is set to its previous value. Otherwise, the behavior is defined in the table defining [StartUpOnOffEnum](#).

This behavior does not apply to reboots associated with OTA. After an OTA restart, the OnOff attribute SHALL return to its value prior to the restart.

1.5.7. Commands

ID	Name	Direction	Response	Access	Conformance
0x00	Off	client ⇒ server	Y	O	M
0x01	On	client ⇒ server	Y	O	!OFFONLY
0x02	Toggle	client ⇒ server	Y	O	!OFFONLY
0x40	OffWithEffect	client ⇒ server	Y	O	LT
0x41	OnWithRecall-GlobalScene	client ⇒ server	Y	O	LT
0x42	OnWith-TimedOff	client ⇒ server	Y	O	LT

1.5.7.1. Off Command

This command allows devices to be turned off.

1.5.7.1.1. Effect on Receipt

On receipt of the Off command, a server SHALL set the OnOff attribute to FALSE.

Additionally, when the OnTime attribute is supported, the server SHALL set the OnTime attribute to 0.

1.5.7.2. On Command

This command allows devices to be turned on.