

1.5.7.2.1. Effect on Receipt

If the OffOnly feature is supported, on receipt of the On command, an UNSUPPORTED_COMMAND failure status response SHALL be sent. Otherwise, on receipt of the On command, a server SHALL set the OnOff attribute to TRUE.

Additionally, when the OnTime and OffWaitTime attributes are both supported, if the value of the OnTime attribute is equal to 0, the server SHALL set the OffWaitTime attribute to 0.

1.5.7.3. Toggle Command

This command allows devices to be toggled.

1.5.7.3.1. Effect on Receipt

If the OffOnly feature is supported, on receipt of the Toggle command, an UNSUPPORTED_COMMAND failure status response SHALL be sent. Otherwise, on receipt of the Toggle command, if the value of the OnOff attribute is equal to FALSE, the server SHALL set the OnOff attribute to TRUE, otherwise, the server SHALL set the OnOff attribute to FALSE.

Additionally, when the OnTime and OffWaitTime attributes are both supported, if the value of the OnOff attribute is equal to FALSE and if the value of the OnTime attribute is equal to 0, the server SHALL set the OffWaitTime attribute to 0. If the value of the OnOff attribute is equal to TRUE, the server SHALL set the OnTime attribute to 0.

1.5.7.4. OffWithEffect Command

The OffWithEffect command allows devices to be turned off using enhanced ways of fading.

The OffWithEffect command SHALL have the following data fields:

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	EffectIdentifier	EffectIdentifierEnum	desc			M
1	EffectVariant	enum8	desc			M

1.5.7.4.1. EffectIdentifier Field

This field specifies the fading effect to use when turning the device off. This field SHALL contain one of the non-reserved values listed in [EffectIdentifierEnum](#).

1.5.7.4.2. EffectVariant Field

This field is used to indicate which variant of the effect, indicated in the EffectIdentifier field, SHOULD be triggered. If the server does not support the given variant, it SHALL use the default variant. This field is dependent on the value of the EffectIdentifier field and SHALL contain one of the non-reserved values listed in either [DelayedAllOffEffectVariantEnum](#) or [DyingLightEffectVariantEnum](#).