

1.8.8.1.2. AlarmsSuppressed Field

This field SHALL indicate the state of suppressed alarm modes, as indicated by the [AlarmsSuppressed](#) attribute, at the time the event was generated.

1.8.8.2. SensorFault Event

This event SHALL be generated when the device registers or clears a fault.

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	SensorFault	SensorFault- Bitmap	all			M

1.8.8.2.1. SensorFault Field

This field SHALL indicate the value of the [SensorFault](#) attribute, at the time this event is generated.

1.9. Mode Select Cluster

This cluster provides an interface for controlling a characteristic of a device that can be set to one of several predefined values. For example, the light pattern of a disco ball, the mode of a massage chair, or the wash cycle of a laundry machine.

The server allows the client to set a mode on the server. A mode is one of a list of options that may be presented by a client for a user choice, or understood by the client, via the semantic tags on the mode.

A semantic tag is either a standard tag within a standard category namespace, or a manufacturer specific tag, within the namespace of the vendor ID of the manufacturer. If there is no semantic tag, the mode is anonymous, and the selection is made by the user solely based on the Label string.

Each cluster ID that indicates this specification SHALL define a distinct purpose for the cluster instance. For example: A LightBlinking cluster ID supports blinking modes for a light (and is described that way).

An anonymous mode SHALL support the derived cluster purpose. A manufacturer specific semantic tag SHALL support the derived cluster purpose. An anonymous mode SHALL NOT replace the meaning of a standard semantic tag, when one exists, for the cluster purpose.

1.9.1. Revision History

The global ClusterRevision attribute value SHALL be the highest revision number in the table below.

Revision	Description
1	Initial revision