

1.10.5.1.2. Value Field

This field SHALL indicate the mode tag within a mode tag namespace which is either manufacturer specific or standard.

1.10.5.2. ModeOptionStruct Type

This is a struct representing a possible mode of the server.

ID	Name	Type	Constraint	Quality	Fallback	Access	Conformance
0	Label	string	max 64	F			M
1	Mode	uint8		F			M
2	ModeTags	list[ModeTagStruct]	max 8	F			M

1.10.5.2.1. Label Field

This field SHALL indicate readable text that describes the mode option, so that a client can provide it to the user to indicate what this option means. This field is meant to be readable and understandable by the user.

1.10.5.2.2. Mode Field

This field is used to identify the mode option.

1.10.5.2.3. ModeTags Field

This field SHALL contain a list of tags that are associated with the mode option. This MAY be used by clients to determine the full or the partial semantics of a certain mode, depending on which tags they understand, using standard definitions and/or manufacturer specific namespace definitions.

The standard mode tags are defined in this cluster specification. For the derived cluster instances, if the specification of the derived cluster defines a namespace, the set of standard mode tags also includes the mode tag values from that namespace.

Mode tags can help clients look for options that meet certain criteria, render the user interface, use the mode in an automation, or to craft help text their voice-driven interfaces. A mode tag SHALL be either a standard tag or a manufacturer specific tag, as defined in each [ModeTagStruct](#) list entry.

A mode option MAY have more than one mode tag. A mode option MAY be associated with a mixture of standard and manufacturer specific mode tags. A mode option SHALL be associated with at least one standard mode tag.

Each mode tag in this field SHALL be distinct from other mode tags in this field. For example, a simplified list containing [Auto, Auto] would not be allowed.

A few examples are provided below.

- A mode named "100%" can have both the High (manufacturer specific) and Max (standard)