

SupportedModes Index	Simplified mode tag list	Reason
1	Cool, MfrTag1	Overlap is ok, the set was made unique by adding a manufacturer specific tag
2	Cool, MfrTag2	Overlap is ok, list is unique

Simplified examples of disallowed ModeTags lists:

SupportedModes Index	Simplified mode tag list	Reason
0	Cool, MfrTag1	Tag set is duplicated
1	MfrTag1, Cool	Tag set is duplicated

1.10.6.2. CurrentMode Attribute

This attribute SHALL indicate the current mode of the server.

The value of this field SHALL match the Mode field of one of the entries in the SupportedModes attribute.

The value of this attribute may change at any time via an out-of-band interaction outside of the server, such as interactions with a user interface, via internal mode changes due to autonomously progressing through a sequence of operations, on system time-outs or idle delays, or via interactions coming from a fabric other than the one which last executed a ChangeToMode.

1.10.6.3. StartUpMode Attribute

This attribute SHALL indicate the desired startup mode for the server when it is supplied with power.

If this attribute is not null, the CurrentMode attribute SHALL be set to the StartUpMode value, when the server is powered up, except in the case when the OnMode attribute overrides the StartUpMode attribute (see [Section 1.10.6.4.1, “OnMode with Power Up”](#)).

This behavior does not apply to reboots associated with OTA. After an OTA restart, the CurrentMode attribute SHALL return to its value prior to the restart.

The value of this field SHALL match the Mode field of one of the entries in the SupportedModes attribute.

If this attribute is not implemented, or is set to the null value, it SHALL have no effect.

1.10.6.4. OnMode Attribute

This attribute SHALL indicate whether the value of CurrentMode depends on the state of the On/Off cluster on the same endpoint. If this attribute is not present or is set to null, there is no dependency, otherwise the CurrentMode attribute SHALL depend on the OnOff attribute in the On/Off cluster as described in the table below: