

Mode Tag Value Range	Range Name	Summary
0x4000 to 0x7FFF	DerivedClusterTags	Derived cluster specific standard values defined in the derived cluster specification.
0x8000 to 0xBFFF	MfgTags	Manufacturer-specific values. For the derived cluster instances, these are manufacturer specific under the derived cluster.

The derived cluster specific standard value definitions SHALL not duplicate the common standard value definitions. For example, a derived cluster specification can't define a mode tag value with the same mode as the common standard tag value of 0x0001 (Quick).

The set of ModeTagStruct Value field values defined in each of the generic or derived Mode Base cluster specifications is called ModeTag.

The following table defines the common ModeTag values.

Mode Tag Value	Name
0x0000	Auto
0x0001	Quick
0x0002	Quiet
0x0003	LowNoise
0x0004	LowEnergy
0x0005	Vacation
0x0006	Min
0x0007	Max
0x0008	Night
0x0009	Day

1.10.8.1. Auto Tag

The device decides which options, features and setting values to use.

1.10.8.2. Quick Tag

The mode of the device is optimizing for faster completion.

1.10.8.3. Quiet Tag

The device is silent or barely audible while in this mode.