

sequence of presses beyond MultiPressMax that MAY be taken in account specially by switches (e.g. to trigger special behavior such as factory reset for which generating events towards the client is not appropriate).

1.13.6. Events

ID	Name	Priority	Quality	Access	Conformance
0x00	Switch-Latched	INFO		V	LS
0x01	InitialPress	INFO		V	MS
0x02	LongPress	INFO		V	MSL
0x03	ShortRelease	INFO		V	MSR
0x04	LongRelease	INFO		V	MSL
0x05	MultiPress-Ongoing	INFO		V	MSM & !AS
0x06	MultiPress-Complete	INFO		V	MSM

1.13.6.1. SwitchLatched Event

This event SHALL be generated, when the latching switch is moved to a new position. It MAY have been delayed by debouncing within the switch.

The data of this event SHALL contain the following information:

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	NewPosition	uint8	0 to (NumberOfPositions - 1)			M

1.13.6.1.1. NewPosition Field

This field SHALL indicate the new value of the CurrentPosition attribute, i.e. after the move.

1.13.6.2. InitialPress Event

This event SHALL be generated, when the momentary switch starts to be pressed (after debouncing).

The data of this event SHALL contain the following information: