

1.13.6.3.1. NewPosition Field

This field SHALL indicate the new value of the CurrentPosition attribute, i.e. while pressed.

1.13.6.4. ShortRelease Event

If the server has the Action Switch (AS) feature flag set, this event SHALL NOT be generated at all, since setting the Action Switch feature flag forbids the Momentary Switch ShortRelease (MSR) feature flag from being set. Otherwise, the following paragraphs describe the situations where this event is generated.

This event SHALL be generated, when the momentary switch has been released (after debouncing).

- If the server has the Momentary Switch LongPress (MSL) feature flag set, then this event SHALL be generated when the switch is released if **no** LongPress event had been generated since the previous InitialPress event.
- If the server does not have the Momentary Switch LongPress (MSL) feature flag set, this event SHALL be generated when the switch is released - even when the switch was pressed for a long time.
- Also see [Section 1.13.7, “Sequence of generated events”](#).

The data of this event SHALL contain the following information:

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	PreviousPosition	uint8	0 to (NumberOfPositions - 1)			M

1.13.6.4.1. PreviousPosition Field

This field SHALL indicate the previous value of the CurrentPosition attribute, i.e. just prior to release.

1.13.6.5. LongRelease Event

This event SHALL be generated, when the momentary switch has been released (after debouncing) and after having been pressed for a long time, i.e. this event SHALL be generated when the switch is released if a LongPress event has been generated since the previous InitialPress event. Also see [Section 1.13.7, “Sequence of generated events”](#).

The data of this event SHALL contain the following information:

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	PreviousPosition	uint8	0 to (NumberOfPositions - 1)			M