

1.13.8.1. Multi-press behavior when ActionsSwitch (AS) feature flag is not set

A switch with the MSM feature flag set but the AS flag unset:

- SHALL generate an InitialPress event at the start of every button press within a button multi-press cycle;
- SHALL generate a ShortRelease event at the end of every button press within a button multi-press cycle if MSR is set;
- SHALL generate a MultiPressOngoing event after the InitialPress event of the second and subsequent presses of a button multi-press cycle;
- SHALL generate a MultiPressComplete at the end of a multi-press cycle, including single presses;
- SHALL NOT (for cluster revision ≥ 2) or SHOULD NOT (for cluster revision < 2) generate any LongPress and LongRelease events within the multi-press cycle.

The MultiPressOngoing event is provided for parties interested in keeping track of the actual presses during the multi-press sequence. The MultiPressComplete event is provided for parties interested in the outcome of the whole sequence: after the multi-press sequence has ended, they will receive the MultiPressComplete event indicating how many times the switch was pressed.

In the figure below, several sequences of user interaction are indicated:

- Single press sequence: after the press and release moments, the InitialPress SHALL be generated, and ShortRelease events SHALL be generated if the MSR feature flag is set. After some further time, when the switch has detected that there is no second press, it SHALL generate MultiPressComplete(1) since it has detected that the sequence consisted of one press. No MultiPressOngoing event SHALL be generated for this case.
- Double press sequence: after each of the press and release moments, the InitialPress SHALL be generated, and ShortRelease events SHALL be generated if the MSR feature flag is set. Additionally, when the switch is pressed for the second time, the MultiPressOngoing(2) event SHALL be generated, as the switch has detected the second press. Note that this event coincides with the second InitialPress event; both SHALL be generated. After some further time, when the switch has detected that there is no third press, it SHALL generate MultiPressComplete(2) since it has detected that the sequence consisted of two presses.
- Triple press sequence: after each press and release moments, the InitialPress SHALL be generated, and ShortRelease events SHALL be generated if the MSR feature flag is set. Additionally, when the switch is pressed for the second time, the MultiPressOngoing(2) event SHALL be generated, as the switch has detected the second press. Note that this event coincides with the second InitialPress event; both SHALL be generated. Additionally, when the switch is pressed for the third time, the MultiPressOngoing(3) event SHALL be generated, as the switch has detected the third press. Note that this event coincides with the third InitialPress event; both SHALL be generated. After some further time, when the switch has detected that there is no fourth press, it SHALL generate MultiPressComplete(3) since it has detected that the sequence consisted of three presses.
 - This case specifically does NOT generate LongPress and LongRelease events within the sequence (even though the figure below illustrates a longer press duration for the second