

Table 4. Resume Compatibility

State Value	State Name	Resume-Compatible
0x00	Stopped	N
0x01	Running	Y
0x02	Paused	Y
0x03	Error	N

A device that is unable to honor the Resume command for any other reason SHALL respond with an [OperationalCommandResponse](#) command with an ErrorStateID of UnableToStartOrResume but take no further action.

Otherwise, on success:

- The OperationalState attribute SHALL be set to the most recent non-Error operational state prior to entering the Paused state.
- The device SHALL respond with an [OperationalCommandResponse](#) command with an ErrorStateID of NoError.

1.14.6.5. OperationalCommandResponse Command

This command SHALL be supported by an implementation if any of the other commands defined by this cluster are supported (i.e. listed in the AcceptedCommandList global attribute). This command SHALL also be supported by an implementation of a derived cluster as a response to any commands that MAY be additionally defined therein.

This command SHALL be generated in response to any of the Start, Stop, Pause, or Resume commands. The data for this command SHALL be as follows:

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0x00	CommandResponseState	ErrorStateStruct	all			M

1.14.6.5.1. CommandResponseState Field

This SHALL indicate the success or otherwise of the attempted command invocation. On a successful invocation of the attempted command, the ErrorStateID SHALL be populated with NoError. See the individual command sections for additional specific requirements on population.

1.14.7. Events

ID	Name	Priority	Access	Conformance
0x00	OperationalError	CRITICAL	V	M