

Value	Name	Summary	Conformance
0x01	Operating	The device is currently operating at the given area	M
0x02	Skipped	The device has skipped the given area, before or during operating at it, due to a SkipArea command, due an out of band command (e.g. from the vendor's application), due to a vendor specific reason, such as a time limit used by the device, or due the device ending operating unsuccessfully	M
0x03	Completed	The device has completed operating at the given area	M

1.17.5.6.1. SelectAreasStatus Type

This data type is derived from enum8.

Value	Name	Summary	Conformance
0x00	Success	Attempting to operate in the areas identified by the entries of the NewAreas field is allowed and possible. The SelectedAreas attribute is set to the value of the NewAreas field.	M
0x01	UnsupportedArea	The value of at least one of the entries of the NewAreas field doesn't match any entries in the SupportedAreas attribute.	M