

A few examples are provided below.

Valid list of areas:

- AreaID=0, LocationName="yellow bedroom", MapID=null
- AreaID=1, LocationName="orange bedroom", MapID=null

Valid list of areas:

- AreaID=5, LocationName="hallway", MapID=1
- AreaID=3, LocationName="hallway", MapID=2

1.17.6.2. SupportedMaps Attribute

This attribute SHALL contain the list of supported maps.

A map is a full or a partial representation of a home, known to the device. For example:

- a single level home MAY be represented using a single map
- a two level home MAY be represented using two maps, one for each level
- a single level home MAY be represented using two maps, each including a different set of rooms, such as "map of living room and kitchen" and "map of bedrooms and hallway"
- a single level home MAY be represented using one map for the indoor areas (living room, bedrooms etc.) and one for the outdoor areas (garden, swimming pool etc.)

Each map includes one or more areas - see the SupportedAreas attribute. In the context of this cluster specification, a map is effectively a group label for a set of areas, rather than a graphical representation that the clients can display to the users. The clients that present the list of available areas for user selection (see the SelectAreas command) MAY choose to filter the SupportedAreas list based on the associated map. For example, the clients MAY allow the user to indicate that the device is to operate on the first floor, and allow the user to choose only from the areas situated on that level.

If empty, that indicates that the device is currently unable to provide this information.

Each entry in this list SHALL have a unique value for the MapID field.

Each entry in this list SHALL have a unique value for the Name field.

NOTE

due to the maximum size of this list and to the fact that the entries MAY include strings (see the Name field of the MapStruct data type), care must be taken by implementers to avoid creating a data structure that is overly large, which can result in significant latency in accessing this attribute.

The value of this attribute MAY change at any time via an out-of-band interaction outside of the server, such as interactions with a user interface.

When updating the SupportedMaps attribute list by deleting entries, or by setting the attribute to an empty list, the SupportedAreas attribute SHALL be updated such that all entries in that list meet the constraints indicated in the description of the SupportedAreas attribute. This MAY result in the