

1.17.7.1.2. Effect on Receipt

If the NewAreas field contains any duplicated entries, the device SHALL operate on only the first instance of an entry in the list.

For example, if the list [1, 2, 2, 3, 2] were received, the device would ignore the duplicated instances of 2 in the list and operate as if the list [1, 2, 3] had been received instead.

If the device determines that it can't operate at all areas from the list, the SelectAreasResponse command's Status field SHALL indicate InvalidSet.

If at least one entry on the NewAreas field doesn't match the AreaID field of any entry of the SupportedAreas list, the SelectAreasResponse command's Status field SHALL indicate UnsupportedArea.

If the current state of the device doesn't allow for the areas to be selected, the SelectAreasResponse command SHALL have the Status field set to InvalidInMode.

Unless the SelectWhileRunning feature indicates that selecting areas is allowed while the device is in a non-idle state, such as operating or paused, the SelectAreasResponse command SHALL have the Status field set to InvalidInMode if this restriction prevents changing the selected areas.

Otherwise, if the device accepts the request, the server will attempt to operate at the areas indicated by the entries of the NewArea field, the SelectAreasResponse command SHALL have the Status field set to Success, and the SelectedAreas attribute SHALL be set to the value of the NewAreas field.

NOTE

The device MAY start to operate immediately or wait until specifically requested to operate. The behavior of the device is manufacturer specific.

If the NewAreas field is the same as the value of the SelectedAreas attribute the SelectAreasResponse command SHALL have the Status field set to Success and the StatusText field MAY be supplied with a human readable string or include an empty string.

1.17.7.2. SelectAreasResponse Command

This command is sent by the device on receipt of the SelectAreas command. This command SHALL have the following data fields:

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	Status	SelectAreasStatus	all			M
1	StatusText	string	max 256			M

1.17.7.2.1. Status Field

If the Status field is set to Success or UnsupportedArea, the server MAY use a non-empty string for the StatusText field to provide additional information. For example, if Status is set to Unsupported