

component of a device that is designed to be replaced, refilled, or emptied when exhausted or full. Examples of resources include filters, cartridges, and water tanks. While batteries fit this definition they are not intended to be used with this cluster. Use the power source cluster for batteries instead.

NOTE

This cluster is not meant to be used for monitoring of the system resources, such as processing, memory utilization, networking properties, etc.

This cluster SHALL be used via an alias to a specific resource type (see [Cluster IDs](#)).

2.8.1. Revision History

The global ClusterRevision attribute value SHALL be the highest revision number in the table below.

Revision	Description
1	Initial revision

2.8.2. Classification

Hierarchy	Role	Scope	PICS Code
Base	Application	Endpoint	REPM

2.8.3. Cluster IDs

The table below is a list of aliased Cluster IDs which represent different resource types and conform to this cluster definition.

ID	Name	PICS
0x0071	HEPA Filter Monitoring	HEPAFREMON
0x0072	Activated Carbon Filter Monitoring	ACFREMON
0x0079	Water Tank Level Monitoring	WTLREPMON

2.8.4. Features

This cluster SHALL support the FeatureMap bitmap attribute as defined below.

Bit	Code	Feature	Conformance	Summary
0	CON	Condition	O	Supports monitoring the condition of the resource in percentage
1	WRN	Warning	O	Supports warning indication