

Bit	Code	Feature	Conformance	Summary
2	CL	ColorLoop	O	Color loop is supported.
3	XY	XY	O	Supports color specification via XY.
4	CT	ColorTemperature	O	Supports specification of color temperature.

3.2.5. Dependencies

3.2.5.1. Coupling color temperature to Level Control

If the Level Control for Lighting cluster identifier 0x0008 is supported on the same endpoint as the Color Control cluster and color temperature is supported, it is possible to couple changes in the current level to the color temperature.

The CoupleColorTempToLevel bit of the Options attribute of the Level Control cluster indicates whether the color temperature is to be linked with the CurrentLevel attribute in the Level Control cluster.

If the CoupleColorTempToLevel bit of the Options attribute of the Level Control cluster is equal to 1 and the ColorMode or EnhancedColorMode attribute is set to 2 (ColorTemperatureMireds) then a change in the CurrentLevel attribute SHALL affect the ColorTemperatureMireds attribute. This relationship is manufacturer specific, with the qualification that the maximum value of the CurrentLevel attribute SHALL correspond to a ColorTemperatureMired attribute value equal to the CoupleColorTempToLevelMinMireds attribute. This relationship is one-way so a change to the ColorTemperatureMireds attribute SHALL NOT have any effect on the CurrentLevel attribute.

In order to simulate the behavior of an incandescent bulb, a low value of the CurrentLevel attribute SHALL be associated with a high value of the ColorTemperatureMireds attribute (i.e., a low value of color temperature in kelvins).

If the CoupleColorTempToLevel bit of the Options attribute of the Level Control cluster is equal to 0, there SHALL be no link between color temperature and current level.

3.2.5.2. Independent transition in hue and saturation

Various commands in this cluster can be used to start transitions in hue and/or saturation.

- When a transition in hue is in progress, and a command to change saturation (MoveSaturation (with MoveMode!=Stop), StepSaturation, MoveToSaturation) is received by the server, this latter command SHALL NOT interrupt the ongoing transition in hue.
- When a transition in saturation is in progress, and a command to change hue (MoveHue (with MoveMode!=Stop), EnhancedMoveHue (with MoveMode!=Stop) StepHue, EnhancedStepHue, MoveToHue, EnhancedMoveToHue) is received by the server, this latter command SHALL NOT