

The movement SHALL be continuous, i.e., not a step function, and the time taken to move to the new hue SHALL be equal to the TransitionTime field.

As hue is effectively measured on a circle, the new hue MAY be moved to in either direction. The direction of hue change is given by the Direction field. If Direction is 'Shortest distance', the direction is taken that involves the shortest path round the circle. This case corresponds to expected normal usage. If Direction is 'Longest distance', the direction is taken that involves the longest path round the circle. This case can be used for 'rainbow effects'. In both cases, if both distances are the same, the Up direction SHALL be taken.

3.2.8.5. MoveHue Command

This command will move the device to the requested hue value using a step rate.

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	MoveMode	MoveModeEnum	all			M
1	Rate	uint8	all			M
2	OptionsMask	OptionsBitmap	desc			M
3	OptionsOverride	OptionsBitmap	desc			M

3.2.8.5.1. MoveMode Field

This field SHALL indicate the mode of movement.

3.2.8.5.2. Rate Field

This field SHALL indicate the rate of movement in steps per second. A step is a change in the device's hue of one unit.

3.2.8.5.3. OptionsMask and OptionsOverride field

These fields SHALL be processed according to section [Use of the OptionsMask and OptionsOverride Fields](#).

3.2.8.5.4. Effect on Receipt

On receipt of this command,

- If the MoveMode field is set to 1 (Up) or 3 (Down):
 - If the Rate field has a value of zero, the command has no effect and a response SHALL be returned with the status code set to INVALID_COMMAND.
 - Otherwise, a device SHALL set the ColorMode attribute to the value 0 (CurrentHueAndCurrentSaturation) and SHALL then move from its current hue in an up or down direction in a continuous fashion, as detailed in the table.