

3.2.8.19.2. Action Field

This field SHALL indicate the action to take for the color loop.

3.2.8.19.3. Direction Field

This field SHALL indicate the direction for the color loop.

3.2.8.19.4. Time Field

This field SHALL indicate the number of seconds over which to perform a full color loop.

3.2.8.19.5. Start Hue Field

This field SHALL indicate the starting hue to use for the color loop.

3.2.8.19.6. OptionsMask and OptionsOverride Fields

These fields SHALL be processed according to section [Use of the OptionsMask and OptionsOverride Fields](#).

3.2.8.19.7. Effect on Receipt

On receipt of this command, the device SHALL first update its color loop attributes according to the value of the UpdateFlags field, as follows.

- If the UpdateDirection sub-field is set to 1, the device SHALL set the ColorLoopDirection attribute to the value of the Direction field.
- If the UpdateTime sub-field is set to 1, the device SHALL set the ColorLoopTime attribute to the value of the Time field.
- If the UpdateStartHue sub-field is set to 1, the device SHALL set the ColorLoopStartEnhancedHue attribute to the value of the StartHue field.
- If the UpdateAction sub-field of the UpdateFlags field is set to 1, the device SHALL adhere to the action specified in the Action field, as follows.
 - If the value of the Action field is set to 0 and the color loop is active, i.e. the ColorLoopActive attribute is set to 1, the device SHALL de-active the color loop, set the ColorLoopActive attribute to 0 and set the EnhancedCurrentHue attribute to the value of the ColorLoopStoredEnhancedHue attribute.
 - If the value of the Action field is set to 0 and the color loop is inactive, i.e. the ColorLoopActive attribute is set to 0, the device SHALL ignore the action update component of the command, i.e. the EnhancedCurrentHue attribute SHALL NOT be updated (contrasting with the case described in the previous bullet).
 - If the value of the Action field is set to 1, the device SHALL set the ColorLoopStoredEnhancedHue attribute to the value of the EnhancedCurrentHue attribute, set the ColorLoopActive attribute to 1 and activate the color loop, starting from the value of the ColorLoopStartEnhancedHue attribute.
 - If the value of the Action field is set to 2, the device SHALL set the ColorLoopStoredEnhancedHue attribute to the value of the EnhancedCurrentHue attribute, set the Color-