

4.2.7.18. Speed Attribute

This attribute specifies the actual speed of the pump measured in RPM. It is updated dynamically as the speed of the pump changes.

If the value is not available (the measurement or estimation of the speed is done in the pump), this attribute will indicate the null value.

Valid range is 0 to 65,534 RPM.

4.2.7.19. LifetimeRunningHours Attribute

This attribute specifies the accumulated number of hours that the pump has been powered and the motor has been running. It is updated dynamically as it increases. It is preserved over power cycles of the pump. If LifeTimeRunningHours rises above maximum value it “rolls over” and starts at 0 (zero).

This attribute is writeable, in order to allow setting to an appropriate value after maintenance. If the value is not available, this attribute will indicate the null value.

Valid range is 0 to 16,777,214 hrs.

4.2.7.20. Power Attribute

This attribute specifies the actual power consumption of the pump in Watts. The value of this attribute is updated dynamically as the power consumption of the pump changes.

This attribute is read only. If the value is not available (the measurement of power consumption is not done in the pump), this attribute will indicate the null value.

Valid range is 0 to 16,777,214 Watts.

4.2.7.21. LifetimeEnergyConsumed Attribute

This attribute specifies the accumulated energy consumption of the pump through the entire lifetime of the pump in kWh. The value of the LifetimeEnergyConsumed attribute is updated dynamically as the energy consumption of the pump increases. If LifetimeEnergyConsumed rises above maximum value it “rolls over” and starts at 0 (zero).

This attribute is writeable, in order to allow setting to an appropriate value after maintenance.

Valid range is 0 kWh to 4,294,967,294 kWh.

This attribute SHALL be null if the value is unknown.

4.2.7.22. OperationMode Attribute

This attribute specifies the operation mode of the pump as defined in [OperationModeEnum](#).

The actual operating mode of the pump is a result of the setting of the attributes OperationMode, ControlMode and the optional connection of a remote sensor. The operation and control is prioritized as shown in the scheme below: