

5.2.6.4. ConfigurationRegisterBitmap Type

This data type is derived from map16.

Bit	Name	Summary	Conformance
0	LocalProgramming	The state of local programming functionality	M
1	KeypadInterface	The state of the keypad interface	M
2	RemoteInterface	The state of the remote interface	M
5	SoundVolume	Sound volume is set to Silent value	M
6	AutoRelockTime	Auto relock time it set to 0	M
7	LEDSettings	LEDs is disabled	M

5.2.6.4.1. LocalProgramming Bit

This bit SHALL indicate the state related to local programming:

- 0 = Local programming is disabled
- 1 = Local programming is enabled

5.2.6.4.2. KeypadInterface Bit

This bit SHALL indicate the state related to keypad interface:

- 0 = Keypad interface is disabled
- 1 = Keypad interface is enabled

5.2.6.4.3. RemoteInterface Bit

This bit SHALL indicate the state related to remote interface:

- 0 = Remote interface is disabled
- 1 = Remote interface is enabled

5.2.6.4.4. SoundVolume Bit

This bit SHALL indicate the state related to sound volume:

- 0 = Sound volume value is 0 (Silent)
- 1 = Sound volume value is equal to something other than 0