

5.2.6.5.3. ClearUsersCredentialsSchedules Bit

This bit SHALL indicate whether the door lock is able to clear Users/Credentials/Schedules locally:

- 0 = This ability is disabled
- 1 = This ability is enabled

5.2.6.5.4. AdjustSettings Bit

This bit SHALL indicate whether the door lock is able to adjust lock settings locally:

- 0 = This ability is disabled
- 1 = This ability is enabled

5.2.6.6. AlarmMaskBitmap Type

This data type is derived from map16.

Bit	Name	Summary	Conformance
0	LockJammed	Locking Mechanism Jammed	M
1	LockFactoryReset	Lock Reset to Factory Defaults	O
3	LockRadioPowerCycled	RF Module Power Cycled	O
4	WrongCodeEntryLimit	Tamper Alarm - wrong code entry limit	PIN RID
5	FrontEscutcheonRemoved	Tamper Alarm - front escutcheon removed from main	O
6	DoorForcedOpen	Forced Door Open under Door Locked Condition	O

5.2.6.7. AlarmCodeEnum Type

This data type is derived from enum8.

This enumeration SHALL indicate the alarm type.

Value	Name	Summary	Conformance
0	LockJammed	Locking Mechanism Jammed	M
1	LockFactoryReset	Lock Reset to Factory Defaults	O