

ID	Name	Type	Constraint	Quality	Fallback	Conformance
2	OperationError	OperationErrorEnum	all			M
3	UserIndex	uint16	all	X		M
4	FabricIndex	fabric-idx	all	X		M
5	SourceNode	node-id	all	X		M
6	Credentials	list[CredentialStruct]	1 to NumberOfCredentialsSupportedPerUser	X		[USR]

5.2.11.4.1. LockOperationType Field

This field SHALL indicate the type of the lock operation that was performed.

5.2.11.4.2. OperationSource Field

This field SHALL indicate the source of the lock operation that was performed.

5.2.11.4.3. OperationError Field

This field SHALL indicate the lock operation error triggered when the operation was performed.

5.2.11.4.4. UserIndex Field

This field SHALL indicate the lock UserIndex who performed the lock operation. This SHALL be null if there is no user id that can be determined for the given operation source.

5.2.11.4.5. FabricIndex Field

This field SHALL indicate the fabric index of the fabric that performed the lock operation. This SHALL be null if there is no fabric that can be determined for the given operation source. This SHALL NOT be null if the operation source is "Remote".

5.2.11.4.6. SourceNode Field

This field SHALL indicate the Node ID of the node that performed the lock operation. This SHALL be null if there is no Node associated with the given operation source. This SHALL NOT be null if the operation source is "Remote".

5.2.11.4.7. Credentials Field

This field SHALL indicate the list of credentials used in performing the lock operation. This SHALL be null if no credentials were involved.