

| ID | Name       | Type  | Constraint   | Quality | Fallback | Access | Conformance |
|----|------------|-------|--------------|---------|----------|--------|-------------|
| 0  | <b>Min</b> | int16 | all          |         |          |        | M           |
| 1  | <b>Max</b> | int16 | Min to 32767 |         |          |        | M           |

#### 5.5.6.9. DimensionStateStruct Type

| ID | Name            | Type               | Constraint | Quality | Fallback | Access | Conformance |
|----|-----------------|--------------------|------------|---------|----------|--------|-------------|
| 0  | <b>Position</b> | percent100ths      | desc       | X       | null     |        | PS          |
| 1  | <b>Latch</b>    | bool               | desc       | X       | null     |        | LT          |
| 2  | <b>Speed</b>    | ThreeLevelAutoEnum | desc       |         | MS       |        | SP          |

##### 5.5.6.9.1. Position Field

This field SHALL indicate the position of the closure, expressed as a percentage from 0.00% to 100.00%.

A null value indicates that the position is not known or is not set.

##### 5.5.6.9.2. Latch Field

This field SHALL indicate the latching state of the closure, as defined in the [OverallCurrentStateStruct Latch Field](#).

A null value indicates that the latch is not known or is not set.

##### 5.5.6.9.3. Speed Field

This field SHALL indicate the current speed of the closure, as defined in the ThreeLevelAutoEnum.

If no speed value has yet been set, the server SHALL select and set one of the speed values defined in the ThreeLevelAutoEnum.

#### 5.5.6.10. LatchControlModesBitmap Type

This data type is derived from map8.

| Bit | Name                    | Summary                      | Conformance |
|-----|-------------------------|------------------------------|-------------|
| 0   | <b>RemoteLatching</b>   | Remote latching capability   | LT          |
| 1   | <b>RemoteUnlatching</b> | Remote unlatching capability | LT          |