

ID	Name	Direction	Response	Access	Conformance
0x01	RenameOutput	client ⇒ server	Y	M	NU

6.5.7.1. SelectOutput Command

Upon receipt, this SHALL change the output on the device to the output at a specific index in the Output List.

Note that when the current output is set to an output of type HDMI, adjustments to volume via a Speaker endpoint on the same node MAY cause HDMI volume up/down commands to be sent to the given HDMI output.

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	Index	uint8	all			M

6.5.7.1.1. Index Field

This SHALL indicate the index field of the [OutputInfoStruct](#) from the OutputList attribute in which to change to.

6.5.7.2. RenameOutput Command

Upon receipt, this SHALL rename the output at a specific index in the Output List.

Updates to the output name SHALL appear in the device's settings menus. Name updates MAY automatically be sent to the actual device to which the output connects.

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	Index	uint8	all			M
1	Name	string	all			M

6.6. Channel Cluster

This cluster provides an interface for controlling the current Channel on a device or endpoint.

This cluster server would be supported on Video Player devices or endpoints that allow Channel control such as a Content App. This cluster provides a list of available channels and provides commands for absolute and relative channel changes. Some of these commands and/or their responses MAY be large (see Large Message Quality under Data Model section in [\[MatterCore\]](#)), but they do not have the Large quality indicator (L) because they can also be transferred over MRP (see Message Reliability Protocol in [\[MatterCore\]](#)) in pages that fit within the MRP MTU limit. However, an implementation MAY leverage a transport like TCP that allows large payloads, if available, to minimize the number of messages required to transfer the corresponding payload.