

6.9.5.2.1. Index Field

This field SHALL indicate the unique index into the list of Inputs.

6.9.5.2.2. InputType Field

This field SHALL indicate the type of input

6.9.5.2.3. Name Field

This field SHALL indicate the input name, such as “HDMI 1”. This field may be blank, but SHOULD be provided when known.

6.9.5.2.4. Description Field

This field SHALL indicate the user editable input description, such as “Living room Playstation”. This field may be blank, but SHOULD be provided when known.

6.9.6. Attributes

ID	Name	Type	Constraint	Quality	Fallback	Access	Conformance
0x0000	InputList	list[InputInfoStruct]				R V	M
0x0001	CurrentInput	uint8	all			R V	M

6.9.6.1. InputList Attribute

This attribute SHALL provide a list of the media inputs supported by the device.

6.9.6.2. CurrentInput Attribute

This attribute SHALL contain the value of the index field of the currently selected [InputInfoStruct](#).

6.9.7. Commands

ID	Name	Direction	Response	Access	Conformance
0x00	SelectInput	client ⇒ server	Y	O	M
0x01	ShowInputStatus	client ⇒ server	Y	O	M
0x02	HideInputStatus	client ⇒ server	Y	O	M
0x03	RenameInput	client ⇒ server	Y	M	NU

6.9.7.1. SelectInput Command

Upon receipt, this command SHALL change the media input on the device to the input at a specific