

8.11.7.1.7. Convection Roast Tag

This mode sets the device into convection roast mode which creates an airflow within the device during the roasting duration.

8.11.7.1.8. Warming Tag

This mode sets the device into a warming mode which begins warming the cavity.

8.11.7.1.9. Proofing Tag

This mode sets the device into proofing mode which creates an environment ready for proofing.

8.11.8. Mode Examples

A few examples of Oven modes and their mode tags are provided below.

- For the "Convection" mode, tags: 0x4001 (Convection)
- For the "Bake" mode, tags: 0x4000 (Bake)
- For the "Bake and Warm" mode, tags: 0x4000 (Bake), 0x4007 (Warming)
- For the "Convection Cook and Clean" mode, tags: 0x4001 (Convection), 0x4004 (Clean)

8.12. Microwave Oven Mode Cluster

This cluster is derived from the Mode Base cluster and defines additional mode tags and name-spaced enumerated values for microwave oven devices.

8.12.1. Revision History

The global ClusterRevision attribute value SHALL be the highest revision number in the table below.

Revision	Description
1	Initial revision
2	Set OnOff feature as disallowed

8.12.2. Classification

Hierarchy	Role	Scope	PICS Code
Mode Base	Application	Endpoint	MWOM

8.12.3. Cluster ID

ID	Name
0x005E	Microwave Oven Mode