

8.13.5.1. CookTime Attribute

This attribute SHALL indicate the total cook time associated with the operation of the device.

This attribute SHALL remain unchanged during the operation of the oven unless the value is changed via a command or out-of-band action.

8.13.5.2. MaxCookTime Attribute

This attribute SHALL indicate the maximum value to which the CookTime attribute can be set.

8.13.5.3. PowerSetting Attribute

This attribute SHALL indicate the power level associated with the operation of the device.

If the MinPower, MaxPower, and PowerStep attributes are not supported:

- The minimum value of this attribute SHALL be 10,
- The maximum value of this attribute SHALL be 100,
- The value SHALL be in even multiples of 10,
- The default value SHALL be 100.

If the MinPower, MaxPower, and PowerStep attributes are supported:

- The value of this attribute SHALL be between MinPower and MaxPower inclusive.
- The value of this attribute SHALL be such that $(\text{PowerSetting} - \text{MinPower}) \% \text{PowerStep} == 0$

8.13.5.4. MinPower Attribute

This attribute SHALL indicate the minimum value to which the PowerSetting attribute that can be set on the server.

8.13.5.5. MaxPower Attribute

This attribute SHALL indicate the maximum value to which the PowerSetting attribute that can be set on the server.

8.13.5.6. PowerStep Attribute

This attribute SHALL indicate the increment of power that can be set on the server.

The value of this attribute SHALL be between 1 and MaxPower inclusive.

The value of this attribute SHALL be such that $(\text{MaxPower} - \text{MinPower}) \% \text{PowerStep} == 0$

For example, if MinPower is 1, MaxPower is 10, and PowerSetting can be set to any integer between MinPower and MaxPower, PowerStep would be set to 1.