

FAILURE.

The command status returned SHALL be SUCCESS if the StartTime in the Forecast is updated. The ESA SHALL update its [Forecast](#) attribute using the new [RequestedStartTime](#) including a new ForecastID, StartTime, EndTime, and [ForecastUpdateReason](#).

9.2.9.4. PauseRequest Command

Allows a client to temporarily pause an operation and reduce the ESAs energy demand.

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	Duration	elapsed-s	desc			M
1	Cause	Adjustment-CauseEnum	all			M

9.2.9.4.1. Duration Field

This field SHALL indicate the duration that the ESA SHALL be paused for. This value SHALL be between the MinPauseDuration and MaxPauseDuration indicated in the ActiveSlotNumber index in the Slots list in the Forecast.

9.2.9.4.2. Cause Field

This field SHALL indicate the cause of the request from the EMS.

9.2.9.4.3. Effect on receipt

On receipt of this command, if the ESA supports **PAU** and the SlotIsPausable field is true in the ActiveSlotNumber index in the Slots list, the [OptOutState](#) permits the specified [Adjustment-CauseEnum](#) (see [OptOutState](#) for details), and the [OptOutState](#) is Online or PowerAdjustActive, the ESA SHALL allow its current operation to be Paused. If the Cause is not permitted, then the command SHALL be rejected with CONSTRAINT_ERROR.

If the ESA SlotIsPausable field is false for the ActiveSlotNumber, then the command SHALL be rejected with FAILURE.

The ESA SHALL validate that the Duration field is within the range of [MinPauseDuration](#) and [MaxPauseDuration](#). If it is outside of this range then the command SHALL be rejected with CONSTRAINT_ERROR.

The command status returned SHALL be SUCCESS if the ESA is paused.

Once the command has been accepted, the ESA SHALL also generate a [Paused](#) Event and the [ESAS-tate](#) SHALL be set to Paused.

The ESA SHALL update its [Forecast](#) to account for the pause, including updating the [ForecastUpdateReason](#) from the Cause field.

Pause timer start The ESA SHALL start a Pause timer based on the value of the Duration field.