

NominalPower	7000	W
MaximumEnergy	42000	Wh

If this ESA supports **SFR** where it does not know the actual power, but has an understanding of the functions that use more energy, it could be requested to use more or less energy using the LoadControl field as follows:

Entry [0] - Turn Down		
StartTime	2023-10-23T16:00:00	
Duration	7200	(2 hours)
LoadControl	-100	(Use less power)

Entry [1] - Turn Up		
StartTime	2023-10-24T00:00:00	
Duration	21,600	(6 hours)
LoadControl	+100	(Use more power)

9.2.9.7.2. Cause Field

This field SHALL indicate the cause of the request from the EMS.

9.2.9.7.3. Effect on receipt

On receipt of this command, if the ESA supports **CON**, and the **OptOutState** permits the specified **AdjustmentCauseEnum** (see **OptOutState** for details), it may be requested to generate a new forecast by a client.

For example the client may be an energy management system which has determined that the peak load on the home should be reduced (for example a grid event) or that there is more local generation available and the solar export power needs to be consumed.

The EMS may not be best placed to make the forecast adjustment because the ESA knows more about its internal operation and system efficiencies.

For example the total energy used when charging a battery faster may result in increased heat losses in the inverter, so the total energy required to charge a battery with 10kWh of stored energy may vary based on charging power.

The ESA SHALL inspect the constraints field to ensure that the constraints defined for that field and its elements are met. The ESA manufacturer may also reject the request if it could cause the user's preferences to be breached (e.g. may cause the home to be too hot or too cold, or a battery to be insufficiently charged).

If the ESA can meet the requested power limits, it SHALL regenerate a new Power Forecast with a new **ForecastID** and **ForecastUpdateReason** from the Cause value.

If an appliance has already begun running a program (and agreed to modify its schedule), it may