

ID	Name	Type	Constraint	Quality	Fallback	Conformance
1	Duration	elapsed-s	all			M
2	EnergyUse	energy-mWh	all			M

9.2.10.2.1. Cause Field

This field SHALL indicate the reason why the power adjustment session ended.

9.2.10.2.2. Duration Field

This field SHALL indicate the number of seconds that the power adjustment session lasted before ending.

9.2.10.2.3. EnergyUse Field

This field SHALL indicate the approximate energy used by the ESA during the session.

For example, if the ESA was on and was adjusted to be switched off, then this SHALL be 0 mWh. If this was a battery inverter that was requested to discharge it would have a negative EnergyUse value. If this was a normal load that was turned on, then it will have positive value.

9.2.10.3. Paused Event

This event SHALL be generated when the ESA enters the Paused state.

There is no data for this event.

9.2.10.4. Resumed Event

This event SHALL be generated when the ESA leaves the Paused state and resumes operation.

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	Cause	CauseEnum	all			M

9.2.10.4.1. Cause Field

This field SHALL indicate the reason why the pause ended.

9.3. Energy EVSE Cluster

Electric Vehicle Supply Equipment (EVSE) is equipment used to charge an Electric Vehicle (EV) or Plug-In Hybrid Electric Vehicle. This cluster provides an interface to the functionality of Electric Vehicle Supply Equipment (EVSE) management.

Devices targeted by this cluster include Electric Vehicle Supply Equipment (EVSE). The cluster generically assumes a signaling protocol (J1772 in NA and IEC61851 in Europe and Asia) between the EVSE and Electric Vehicle (EV) that utilizes a pilot signal to manage the states of the charging