

SHALL be returned with a NULL value.

9.3.8.18. BatteryCapacity Attribute

This attribute SHALL indicate the capacity of the EV battery in mWh. This value is always positive.

9.3.8.19. VehicleID Attribute

This attribute SHALL indicate the vehicle ID read by the EVSE via ISO-15118 using the **PNC** feature, if the EVSE supports this capability.

The field may be based on the e-Mobility Account Identifier (EMAID).

A null value SHALL indicate that this is unknown.

9.3.8.20. Session Attributes

The following set of attributes provides information about a charging session, defined as the period from the EVSE detecting an EV plug-in to when it is unplugged.

NOTE

the session attributes hold their values from the previous session and are reset when the next plug-in event happens.

Whenever the State leaves the NotPluggedIn state and moves to any 'Plugged' state (see the [State](#) attribute), the SessionID attribute SHALL be incremented. The SessionDuration, SessionEnergyCharged and SessionEnergyDischarged attributes SHALL be reset to zero.

9.3.8.20.1. SessionID Attribute

This attribute SHALL indicate a unique identifier for the current or last session. A value of null indicates no sessions have occurred. The SessionID SHALL be incremented each time a plugin is detected. A session begins when the vehicle is plugged in and ends when the vehicle is unplugged.

SessionIDs are allowed to roll over, although the range of SessionID is a large number and it is unlikely that the EVSE will have this many sessions in its lifetime unless there is a electrical fault causes sessions to be detected at a rapid rate.

If there is no session in progress, the Session ID attribute will remain at the value for the last session.

9.3.8.20.2. SessionDuration Attribute

This attribute SHALL indicate the duration in seconds for the current or last charging session. A default value of null indicates no sessions have occurred. A charge session begins when the vehicle is plugged in and ends when the vehicle is unplugged.

The SessionDuration can be calculated from the start time of the session. Manufacturers SHALL ensure this can be correctly calculated if there has been an power failure or reboot since the start of the session.

Changes to this attribute SHALL only be marked as reportable in the following cases: