

Mode Tag Value	Name
0x4001	TimeOfUse
0x4002	SolarCharging
0x4003	V2X

9.4.7.1.1. Manual Tag

While in modes with this tag, and once enabled with the EnableCharging command, the EVSE will permit charging based on demand from the EV.

9.4.7.1.2. TimeOfUse Tag

While in modes with this tag, and once enabled with the EnableCharging command, the EVSE will attempt to automatically start charging based on the user's charging targets (for example, set based on a Time of Use tariff to charge at the cheapest times of the day).

9.4.7.1.3. SolarCharging Tag

While in modes with this tag, and once enabled with the EnableCharging, the EVSE will attempt to automatically start charging based on available excess solar PV generation, limiting the charging power to avoid importing energy from the grid.

9.4.7.1.4. V2X Tag

While in modes with this tag, and once enabled with the EnableDischarging command, the EVSE will permit discharging based on the current charge state of the EV, and its control from an associated Device Energy Management cluster.

NOTE

being in a mode with this tag set or not does not affect the handling of the EnableDischarging command by the Energy EVSE cluster, but once enabled, only modes with this tag enable the discharging to actually occur.

9.4.8. Mode Examples

A few examples of EVSE modes and their mode tags are provided below.

- For the "Manual" mode, tags: 0x4000 (Manual)
- For the "Auto-scheduled" mode, tags: 0x4001 (TimeOfUse)
- For the "Solar" mode, tags: 0x4002 (SolarCharging)
- For the "Auto-scheduled with Solar charging" mode, tags: 0x4001 (TimeOfUse), 0x4002 (SolarCharging)
- For the "Vehicle-to-home with Solar charging" mode, tags: 0x4002 (SolarCharging), 0x4003 (V2X)

9.5. Water Heater Management Cluster

This cluster is used to allow clients to control the operation of a hot water heating appliance so that