

| ID     | Name                  | Type | Constraint | Quality | Fallback | Access | Conformance |
|--------|-----------------------|------|------------|---------|----------|--------|-------------|
| 0x0000 | <b>SupportedModes</b> |      |            |         |          |        |             |
| 0x0001 | <b>Current-Mode</b>   |      |            |         |          |        |             |
| 0x0002 | <b>StartUp-Mode</b>   |      |            |         |          |        | X           |
| 0x0003 | <b>OnMode</b>         |      |            |         |          |        | X           |

#### 9.8.6.1. SupportedModes Attribute

At least one entry in the SupportedModes attribute SHALL include the NoOptimization mode tag in the ModeTags field.

At least one entry in the SupportedModes attribute SHALL include the LocalOptimization mode tag in the ModeTags field list.

At least one entry in the SupportedModes attribute SHALL include the GridOptimization mode tag in the ModeTags field list.

An entry in the SupportedModes attribute that includes one of an DeviceOptimization, LocalOptimization, or GridOptimization tags SHALL NOT also include NoOptimization tag.

#### 9.8.7. Derived Cluster Namespace

This namespace includes definitions for data associated exclusively with the derived cluster.

##### 9.8.7.1. Mode Tags

The following table defines the base and derived-cluster-specific ModeTag values.

| Mode Tag Value | Name             |
|----------------|------------------|
| 0x0000         | <b>Auto</b>      |
| 0x0001         | <b>Quick</b>     |
| 0x0002         | <b>Quiet</b>     |
| 0x0003         | <b>LowNoise</b>  |
| 0x0004         | <b>LowEnergy</b> |
| 0x0005         | <b>Vacation</b>  |
| 0x0006         | <b>Min</b>       |
| 0x0007         | <b>Max</b>       |
| 0x0008         | <b>Night</b>     |
| 0x0009         | <b>Day</b>       |