

11.2.7.22. **HardPrivacyModeOn** Attribute

This attribute indicates the current value of the hard privacy mode for all streams. This is controlled via a physical button or switch, potentially. A value of TRUE indicates that all streams are currently paused. When FALSE, the streams MAY resume if they are not already paused by their corresponding soft privacy mode.

11.2.7.23. **NightVision** Attribute

This attribute indicates the currently selected Night Vision mode. A value of Off means the device will never activate its Night Vision mode of operation. A value of On means the Night Vision mode of operation is always active. A value of Auto means the device will automatically move between active and inactive based on the light level it detects.

11.2.7.24. **NightVisionIllum** Attribute

This attribute indicates the currently selected the Night Vision Illumination mode. A value of Off means the device will never activate its built-in Night Vision Illumination. A value of On means the built-in Night Vision Illumination is always active. A value of Auto means the device will automatically enable its built-in Night Vision Illumination based on the light level it detects.

11.2.7.25. **Viewport** Attribute

This attribute SHALL be a [ViewportStruct](#) representing the viewport to apply to all streams.

The coordinate values represent the upper left corner and lower right corner coordinates of the source rectangle on the sensor. The coordinate values are within the two-dimensional Cartesian plane of size [SensorWidth](#) and [SensorHeight](#) (See [VideoSensorParamsStruct](#) in the [VideoSensorParams](#)) with the origin (0,0) being the upper left corner, positive X and Y values moving right and down across the Cartesian plane respectively, and ([SensorWidth](#), [SensorHeight](#)) being the lower right corner.

When changing the Viewport, the aspect ratio of the sensor as indicated in the [VideoSensorParams](#) attribute SHOULD be preserved.

After a factory reset, this SHALL default to {0, 0, [SensorWidth](#),[SensorHeight](#)}, using the [SensorWidth](#) and [SensorHeight](#) fields from the [VideoSensorParams](#) attribute.

When this attribute is changed, all Viewport values found in [DPTZStreams](#) SHALL be updated to the new values set here.

11.2.7.25.1. **Example**

The following figure shows an example of a 1920x1080 viewport on a 2592x1944 (i.e. 5MP) sensor.