

- If *VideoStreamID* is present and is null and [AllocatedVideoStreams](#) is empty:
 - Fail the command with the status code `INVALID_IN_STATE`, and end processing with no other side effects.
- If *AudioStreamID* is present and is not null and does not match a value in [AllocatedAudioStreams](#):
 - Fail the command with the status code `DYNAMIC_CONSTRAINT_ERROR`, and end processing with no other side effects.
- If *AudioStreamID* is present and is null and [AllocatedAudioStreams](#) is empty:
 - Fail the command with the status code `INVALID_IN_STATE`, and end processing with no other side effects.
- If *SFrameConfig* is present:
 - If the [CipherSuite](#) field of the passed in *SFrameConfig* is not a supported value:
 - Fail the command with the status code `DYNAMIC_CONSTRAINT_ERROR`, and end processing with no other side effects.
 - If the length of the [BaseKey](#) field of the passed in *SFrameConfig* does not match the expected length for a key using the [CipherSuite](#):
 - Fail the command with the status code `DYNAMIC_CONSTRAINT_ERROR`, and end processing with no other side effects.
- For each URL in the [URLs](#) field of each [ICEServerStruct](#) in the passed in *ICEServers*:
 - If the URL scheme is `turns` or `stuns`, and the UTCTime attribute of the Time Synchronization cluster is null:
 - Fail the command with the status code `INVALID_IN_STATE`, and end processing with no other side effects.
- Create a new [WebRTCSessionID](#)
- Create a new [WebRTCSessionStruct](#) associated with the accessing fabric, populated with the passed in values from this command, the *OriginatingEndpointID* field as the [PeerEndpointID](#), and the accessing Peer Node ID entry stored in the Secure Session Context (See Chapter 4 Secure Channel, Secure Session Context section, in [\[MatterCore\]](#)) as the [PeerNodeID](#). The [PeerNodeID](#), [PeerEndpointID](#) and the associated fabric, SHALL be used as the destination for all commands for the corresponding [WebRTCSessionID](#).
- If in [standby mode](#):
 - Respond with a [SolicitOfferResponse](#) with [DeferredOffer](#) set to `TRUE`.
 - Perform device specific steps to exit standby mode. This SHALL take less than 30 seconds.
- Else:
 - Respond with a [SolicitOfferResponse](#) with [DeferredOffer](#) set to `FALSE`.
- If *VideoStreamID* is present and is null:
 - Automatically select an existing [video stream](#) per the [Resource Management and Stream Priorities](#).
 - Store the used *VideoStreamID* in the [WebRTCSessionStruct](#)