

ID	Name	Direction	Response	Access	Quality	Conformance
0x04	SetTransportStatus	client ⇒ server	Y	M F		M
0x05	ManuallyTriggerTransport	client ⇒ server	Y	O F		M
0x06	FindTransport	client ⇒ server	FindTransportResponse	O F	L	M
0x07	FindTransportResponse	server ⇒ client	N		L	M

11.7.9.1. AllocatePushTransport Command

This command SHALL allocate a transport and return a [PushTransportConnectionID](#).

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	TransportOptions	TransportOptionsStruct				M

11.7.9.1.1. TransportOptions Field

This field SHALL represent the configuration options of the transport to be allocated.

11.7.9.1.2. Effect on Receipt

The following process SHALL be followed when the server receives this command:

- If the UTCTime attribute of the Time Synchronization cluster is null:
 - Fail the command with the cluster-specific status code of InvalidTime, and end processing with no other side effects.
- If an entry for the [TLSEndpointID](#) field, of the passed in *TransportOptions*, is not found in the ProvisionedEndpoints list attribute of the TLS Client Management Cluster:
 - Fail the command with the cluster-specific status code of InvalidTLSEndpoint, and end processing with no other side effects.
- If the associated fabric of that entry does not match the accessing fabric:
 - Fail the command with the cluster-specific status code of InvalidTLSEndpoint, and end processing with no other side effects.
- If that entry does not contain a valid non-null CCDID:
 - Fail the command with the cluster-specific status code of InvalidTLSEndpoint, and end pro-