

11.7.9.6.4. UserDefined Field

This field SHALL be an octet string representing arbitrary format user defined metadata that will be included in the recording via the [UserDefined Field](#) field of [AVMetadataStruct](#). The format and meaning of this field is not defined in this specification and is up to the users, vendors, or ecosystems deploying it.

11.7.9.6.5. Effect on Receipt

The following process SHALL be followed when the server receives this command:

- If the UTCTime attribute of the Time Synchronization cluster is null:
 - Fail the command with the cluster-specific status code of InvalidTime, and end processing with no other side effects.
- If no mapping can be found for the ConnectionID:
 - Fail the command with the status code NOT_FOUND, and end processing with no other side effects.
- If the associated fabric of the entry in the [CurrentConnections](#) attribute which is identified by ConnectionID is not the accessing fabric:
 - Fail the command with the status code NOT_FOUND, and end processing with no other side effects.
- If [HardPrivacyModeOn](#) is true:
 - Fail the command with the status code INVALID_IN_STATE, and end processing with no other side effects.
- If [SoftLivestreamPrivacyModeEnabled](#) is true and [StreamUsage Field](#) for the ConnectionID is [LiveView](#):
 - Fail the command with the status code INVALID_IN_STATE, and end processing with no other side effects.
- If [SoftRecordingPrivacyModeEnabled](#) is true and [StreamUsage Field](#) for the ConnectionID is [Recording](#) or [Analysis](#):
 - Fail the command with the status code INVALID_IN_STATE, and end processing with no other side effects.
- If the transport is already transmitting:
 - Fail the command with the status code BUSY, and end processing with no other side effects.
- If the [TransportStatus](#) of the push transport is Inactive:
 - Fail the command with a cluster-specific status code of InvalidTransportStatus, and end processing with no other side effects.
- If the trigger type for the specified transport is [Continuous](#):
 - Fail the command with a cluster-specific status code of InvalidTriggerType, and end processing with no other side effects.
- If the trigger type for the specified transport is [Command](#) and the TimeControl field is not present: