

Revision	Description
1	Initial revision
2	Added Commissioner Control Cluster and Fabric-Synchronization Condition.

11.2.2. Classification

Device Type ID	Device Type Name	Superset Of	Class	Scope
0x000E	Aggregator		Simple	Endpoint

11.2.3. Conditions

This device type MAY support the following conformance conditions as defined below.

Condition	Description
FabricSynchronization	See description below.

See the Base Device Type definition for additional conformance tags.

11.2.3.1. FabricSynchronization Condition

The FabricSynchronization condition applies when there is a Commissioner Control Cluster on this endpoint with a SupportedDeviceCategories attribute with the FabricSynchronization bit set.

11.2.4. Cluster Requirements

Each endpoint supporting this device type SHALL include these clusters based on the conformance defined below.

Cluster ID	Cluster Name	Client/Server	Quality	Conformance
0x0025	Actions	Server		O
0x0003	Identify	Server		O
0x0751	Commissioner Control	Server		FabricSynchronization

The Identify cluster SHOULD be used in case this device type is used to represent a Bridge which has a mechanism to identify itself to the user (e.g. blinking LED on the bridge itself).

For the Identify-functionality of the individual bridged devices, see the Identify cluster on the endpoint for a bridged device.

11.2.5. Endpoint Composition

An Aggregator endpoint's Descriptor cluster PartsList attribute SHALL list the collection of all end-