

points aggregated by the Aggregator device type, i.e. the full-family pattern defined in the System Model specification.

11.2.5.1. Multiple aggregators

When a Node has multiple instances of the Aggregator device type, the composition SHALL comply with one of the following two patterns for any given pair (A,B) of endpoints with the Aggregator device type:

- **No overlap:** The endpoints in the PartsList attribute of Aggregator A do not appear in the PartsList attribute of Aggregator B, and vice versa.
 - Example: A Node which bridges to two non-Matter independent technologies (e.g. Zigbee and Z-Wave), see the aggregators on endpoints 11 and 31 in the figure below - their lists of endpoints (12-14, 21-23 versus 32-33) do not overlap.
- **Strict subset:** The endpoint where aggregator B is exposed and all endpoints in its PartsList attribute (the subset) are included in the PartsList attribute of Aggregator A (the superset).
 - This maintains the rule that there SHALL be a single path from the Root Node to each endpoint (see [System Model](#)).
 - Example: A Node which implements a bridge to Zigbee, and one of those Zigbee devices is connected to a string of DALI lights, which can be addressed individually and thus this Zigbee/DALI device functions as a bridge from Zigbee to DALI; in the figure below one can see that the endpoints for the Zigbee/DALI bridge listed in the PartsList of the aggregator on endpoint 14 (21-23) form a strict subset of the endpoints for the Zigbee bridge in the PartsList of the aggregator on endpoint 11 (12-14, 21-23), and the endpoint 14 of the "subset" aggregator is included in the PartsList of the "superset" aggregator on endpoint 11.