			Values : 0 ~ 64999

URI	<BaseURL>/v1/netusb/setSearchString
Method	POST
Example Request (URI)	http://{host}/YamahaExtendedControl/v1/netusb/setSearchString

Example Request (json)	{
	   "list_id":"auto_complete",
	   "string":"michael"
	}

Response Parameters

name	type	description
response_code	integer	0: Successful request / Others: Error Refer to "Response Code List" for details

Example Response	{
	   "response_code":0
	}

7.12. recallPreset

For recalling a content preset

Request Parameters

name	type	required	description
zone	string	yes	Specifies station recalling zone. This causes input change in specified zone Values: "main" / "zone2" / "zone3" / "zone4"
num	integer	yes	Specifies Preset number Value: one in the range gotten via /system/getFeatures

URI	<BaseURL>/v1/netusb/recallPreset?zone=<zone>&num=<num>
Method	GET
Example Request	http://{host}/YamahaExtendedControl/v1/netusb/recallPreset?zone=main&num=13

Response Parameters

name	type	description
response_code	integer	0: Successful request / Others: Error Refer to "Response Code List" for details

Example Response	{
	   "response_code":0
	}

7.13. storePreset

For registering current content to a preset. Presets are common use among Net/USB related