

```

<eventSubURL>/ConnectionManager/event</eventSubURL>
</service>
</serviceList>
<presentationURL>http://192.168.10.103/</presentationURL>
</device>
<yamaha:X_device>
  <yamaha:X_URLBase>http://192.168.10.103:80/</yamaha:X_URLBase>
  <yamaha:X_serviceList>
    <yamaha:X_service>

<yamaha:X_specType>urn:schemas-yamaha-com:service:X_YamahaRemoteControl:1</yamaha:X
_specType>
  <yamaha:X_controlURL>/YamahaRemoteControl/ctrl</yamaha:X_controlURL>
  <yamaha:X_unitDescURL>/YamahaRemoteControl/desc.xml</yamaha:X_unitDescURL>
  </yamaha:X_service>
  <yamaha:X_service>

<yamaha:X_specType>urn:schemas-yamaha-com:service:X_YamahaExtendedControl:1</yamaha
:X_specType>
  <yamaha:X_yxcControlURL>/YamahaExtendedControl/v1/</yamaha:X_yxcControlURL>
  <yamaha:X_yxcVersion>0801</yamaha:X_yxcVersion>
  </yamaha:X_service>
  </yamaha:X_serviceList>
  </yamaha:X_device>
</root>

```

13.3. Event Process

Events are spread out as UDP unicast. Retrieve necessary info by polling because of UDP packet loss.

(Ex) getStatus, getPlayInfo

13.4. Stereo Pair

Establish Stereo Pair setting by operating Devices. Stereo Pair setting is established as following.



Confirm Stereo Pair status.

Request

http://{DeviceA}/YamahaExtendedControl/v1/system/getStereoPairInfo

Response

```

{
  "response_code":0,
  "status":"master_left",
  "pair_info":{

```