

### 4.30. setHdmiOut3

For setting HDMI OUT 3 terminal output status

#### Request Parameters

name	type	required	description
enable	boolean	yes	Specifies HDMI OUT 3 terminal output status

URI	<BaseURL>/v1/system/setHdmiOut3?enable=<enable>		
Method	GET		
Example Request	http://{host}/YamahaExtendedControl/v1/system/setHdmiOut3?enable=true		

#### Response Parameters

name	type	description
response_code	integer	0: Successful request / Others: Error Refer to <a href="#">“Response Code List”</a> for details

Example Response	{ "response_code":0 }
------------------	-----------------------------

### 4.31. getNameText

For retrieving text information of Zone, Input, Sound program. If they can be renamed, can retrieve text information renamed.

#### Request Parameters

name	type	required	description
Id	string	no	Specifies ID. If no ID is specified, retrieve all information of Zone, Input, Sound program. Refer to <a href="#">“All ID List”</a> for details

URI	<BaseURL>/v1/system/getNameText?id=<id>		
Method	GET		
Example Request	http://{host}/YamahaExtendedControl/v1/system/getNameText?id=main		

#### Response Parameters (No ID is specified)

name	type	description
response_code	integer	0: Successful request / Others: Error Refer to <a href="#">“Response Code List”</a> for details
zone_list	array	Returns a list of Zone
- id	string	Returns Zone ID
- text	string	Returns text information related to Zone ID
input_list	array	Returns a list of Input
- id	string	Returns Input ID
- text	string	Returns text information related to Input ID
sound_program_list	array	Returns a list of Sound program
- id	string	Returns Sound Program ID